Micro Ohm Meter

Model: 53C

Application:

- Communication Cable
- Transformer , Motors, Coil Manufacturer
- Instrumentation Cable
- Transmission / Distribution
- Component Manufacturer
- Current Transformer Manufacturer
- Test Laboratories
- College Laboratories

Features

- True Four Terminal Measurement
- Regulated and Highly stable 1 Amp Current Source
 3 ½ Digital LED Display
- 1uOhm resolution on 2000 uOhm range
- Stable and fast measurement



Range	Current (approx)	Resolution	Accuracy
1999 μΩ	1A	1μΩ	<u>+</u> 0.5% of rdg <u>+3</u> Digits
19.99 m Ω	1A	0.01 m Ω	<u>+</u> 0.5% of rdg <u>+3</u> Digits
199.9 m Ω	1A	0.1 m Ω	<u>+</u> 0.5% of rdg <u>+3</u> Digits
1999 m Ω	1A	1 m Ω	<u>+</u> 0.5% of rdg <u>+</u> 2 Digits
19.99 Ω	100mA	0.01Ω	<u>+</u> 0.5% of rdg <u>+</u> 2 Digits
199.9 Ω	10mA	0.1Ω	<u>+</u> 0.5% of rdg <u>+</u> 2 Digits
1999 Ω	1mA	1Ω	<u>+</u> 0.5% of rdg <u>+</u> 2 Digits
19.99 ΚΩ	0.1mA	0.01 K Ω	<u>+</u> 0.5% of rdg <u>+</u> 2 Digits

Technical Specification

Range : 1 uOhm - 19.99 KOhm

Accuracy : ±0.5% of reading ± 5 Digit

Display : 3 ½ Digit LED Display

Power Supply : 230V AC, 50Hz, 1 Phase

Standard Accessories

- One set of Test leads (1 meters) with Crocodile clips
- Mains Cord
- User Manual

To keep pace with the latest technology Quadrant Measurements Pvt. Ltd. reserves the right to update it's system. Hence, information in the brochure is likely to change without notice.

